

# 3 1/2 DIGIT MINIATURE PANEL METERS

## STANDARD LED



**S I** <sup>1</sup> 4 <sup>2</sup> 6 <sup>3</sup> X <sup>4</sup> X <sup>5</sup> X

1. MOUNTING & CASE:

4: Window Mount  
(Bezel Mount Kit Included)

2. CONNECTION:

6: 10 Pins

3. DISPLAY OPTIONS:

8: Green LED

9: Red LED

4. INPUT RANGE:

0: 199.9mV DC

1: 1.999V DC

2: 19.99V DC

5. METER POWER:

4: 5V DC

5: ±5V DC

## BIGDIGIT LED



**S I** <sup>1</sup> D <sup>2</sup> X <sup>3</sup> X <sup>4</sup> X <sup>5</sup> X

1. MOUNTING & CASE:

D: 1/8 DIN CASE  
(NEMA4 RAGED)

2. CONNECTION:

4: Screw Terminal

6: 10 Pins

3. DISPLAY OPTIONS:

8: Green LED

9: Red LED

4. INPUT RANGE:

A: Amp DC  
(200uA, 2mA, 20mA, 200mA user selectable)

B: Volt DC  
(200mV, 2V, 20V, 200V user selectable)

5. METER POWER:

4: 5V DC or 9V/12V